



Data Sheet 4540009

Product: SmartPlug 16A
EI-number: 4540009
Mat.no: EKO07699
EAN:
Packing:
Color: White



Product description: The SmartPlug 16A is used as plug adapter to control various electrical devices, for example floor lamps, radios, electrical heaters or coffee machines.
The plug can also monitor energy consumption of plugged-in devices. It can be controlled by the ELKO Smart-App through the ELKO SmartHUB, wirelessly through room control or by manually pressing the device.
Functions:
Switching on and off plugged-in devices manually and remotely via app
Pairing to other devices (without gateway ELKO SmartHUB)
Setting a timer or a time schedule (via app)
Visibility of load status (via app)
Monitoring and visualisation of energy consumption (via app)

Technical specifications: Maximum load:
- LED lamp: 100 W
- Incandescent and halogen lamp: 3680 W
- Motor: 300 W
Nominal voltage: 220-240 V AC, 50 Hz
Nominal current: 16 A max
Standby Maximum: 0.5 W
Fuse protection: 16 A circuit breaker
Frequency band: 2.4 GHz
Transmission capacity: Maximum 2.5 mW
IP degree: IP20
Operating temperature: 0 °C to 35 °C
Dimensions (H x W x D): 60 x 60 x 65 mm
Installation: Place the plug in socket outlets that are not hidden behind large objects or furniture that reduce the radio reception, like refrigerators or cabinets
Radio communication: Zigbee 3.0

ELKO AS

E-mail: elko@elko.no
Internet: www.elko.no
Bank: 6219.05.15880
Org.no.: NO 911 382 563 MVA

ELKO Front office
Sandstuveien 68, NO-0680 Oslo
P.O.Box 6598 Etterstad, NO-0607 Oslo
Tel.: +47 67 80 73 00
Fax: +47 67 80 73 01

ELKO Plant
Sporvind Industriområde, NO-3340 Åmot
Tel.: +47 32 78 91 00
Fax: +47 32 78 91 01

ELKO AS

E-mail: elko@elko.no
Internet: www.elko.no
Bank: 6219.05.15880
Org.no.: NO 911 382 563 MVA

ELKO Front office
Sandstuveien 68, NO-0680 Oslo
P.O.Box 6598 Etterstad, NO-0607 Oslo
Tel.: +47 67 80 73 00
Fax: +47 67 80 73 01

ELKO Plant
Sporpind Industriområde, NO-3340 Åmot
Tel.: +47 32 78 91 00
Fax: +47 32 78 91 01