



Data Sheet 6210340

Product: ELKO Smart smoke alarm battery
EI-number: 6210340
Mat.no: EKO09761
EAN:
Packing:
Color:



Product description: The Smart Smoke Alarm - Battery is a design pearl and uses a photoelectric sensor to detect the smoke generated by fire. When connected to the ELKO Smart System, the device sends the notifications via the ELKO Smart app. It can also trigger signals through other products (for example, flashlights) connected to the ELKO Smart system. The smoke alarm can be temporarily deactivated to avoid false alarm when cooking etc. An additional temperature sensor then still provides basic protection.

Technical specifications: EKO09761
Battery life 10 years (not replaceable)
Operating current =70 mA
Sensing type Photoelectric. This alarm contains NO radioactive material.
Interconnecting RF+Zigbee, max. 40 devices in one network
Operating frequency Zigbee: 2405 - 2480 MHz
RF: 868 MHz
Wireless range Zigbee: 40 m line of sight
RF: 50 m line of sight
Horn level 85 dB at 3 m
Hush mode duration 10 minutes
LED brightness levels High / Low
Alarm memory 72 hours
Temperature for alarm If temp > 57 °C
Environment
Operating temperature 0 °C to 45 °C
Ambient humidity 5 % to 95 %
Complementary
Dimensions (H x W x D) 89 x 89 x 33.5 mm
Installation Mount on ceiling and wall only
Certification
Zigbee 3.0, CE (EN14604:2005+AC2008)

ELKO AS

E-mail: elko@elko.no
Internet: www.elko.no
Bank: 6219.05.15880
Org.no.: NO 911 382 563 MVA

ELKO Front office
Sandstuveien 68, NO-0680 Oslo
P.O.Box 6598 Etterstad, NO-0607 Oslo
Tel.: +47 67 80 73 00
Fax: +47 67 80 73 01

ELKO Plant
Sporvind Industriområde, NO-3340 Åmot
Tel.: +47 32 78 91 00
Fax: +47 32 78 91 01

ELKO AS

E-mail: elko@elko.no
Internet: www.elko.no
Bank: 6219.05.15880
Org.no.: NO 911 382 563 MVA

ELKO Front office
Sandstuveien 68, NO-0680 Oslo
P.O.Box 6598 Etterstad, NO-0607 Oslo
Tel.: +47 67 80 73 00
Fax: +47 67 80 73 01

ELKO Plant
Sporpind Industriområde, NO-3340 Åmot
Tel.: +47 32 78 91 00
Fax: +47 32 78 91 01